

Set 820 S RF

Audiology | Wireless Radio Frequency Receiver for TV Sound Transmission

Cat. No. 009373

Description

RF stereo receiver for use with the TR 820 RF stereo transmitter or an RF audio transmission system. The RR 820 S features an audio output for connecting a pair of headphones, an induction neck loop, induction couplers or a hearing aid with audio input. The receiver features a large, easy-to-use volume control and an integrated clip for attaching it to the clothing.



Technical Data System

Colour	blue/anthracite
Modulation.....	FM, stereo
Receiving frequencies.....	863.25 – 863.75 MHz
Frequency selection	frequency search tuning
AF frequency response.....	40 Hz – 15 kHz
THD	< 2 %
Signal-to-noise ratio60 dBA _{rms}
Max. output level.....	> 700 mV at 32 Ω
AF output	3.5 mm stereo jack socket
Operating time.....	> 5 h
Power supply	2.4 V DC via BA 151 accupack
Weight (w/o accupack).....	35 g
Dimensions	95 x 63 x 35 mm

Features

- Individually adjustable to the listener's hearing
- Large, ergonomic volume control
- Integrated attachment clip
- 3.5 mm Ø stereo jack socket for connecting headphones, induction accessories or hearing aids with audio input
- Automatic transmitter search tuning
- *Delivery includes:* 1 RR 820 S stethoset receiver
1 BA 151 accupack

Recommended Accessories

- | | |
|---|-----------------|
| ■ BA 151 Spare accupack | Cat. No. 004146 |
| ■ L 151-2 Charger | Cat. No. 004457 |
| ■ TR 820 (European version) Transmitter | Cat. No. 004984 |
| ■ TR 820-UK (UK version) | Cat. No. 004992 |
| ■ MKE 800 TV, TV microphone | Cat. No. 004995 |
| ■ HD 25 SP-1 Dynamic headphones | Cat. No. 004173 |
| ■ EZI 120 Induction coupler | Cat. No. 003448 |
| ■ EZT 1011 Induction neck loop | Cat. No. 001954 |

Product Variants

- Set 820 S-UK as Set 820 S, but with UK plug-in mains unit and MKE 800 TV microphone Cat. No. 009374